# SONY

SONY

# PXW-FS7 Solid-State Memory Camcorder XOC/M XAVC

Convertien and

0



### The ideal documentary camera

PXW-FS7.

Professionals are greeting the Sony PXW-FS7 with surprise, appreciation and excitement. And for good reason. The camera reflects years of conversations we've had with documentarians on viewfinder placement, grip design, balance and ergonomics. It also reflects Sony's expertise in 4K<sup>i</sup> and HD codecs, Super 35 sensors and memory recording. The result is the ideal camcorder for cinéma vérité documentaries, magazine shows, reality TV, unscripted TV and more.



It shoots in 4K<sup>i</sup> at up to 60p<sup>ii</sup> or Full HD XAVC Intra at a high frame rate of up to 180 fps. Selectable recording formats also include XAVC Long, which supports 1080/60p with 4:2:2 10-bit recording and the legacy MPEG-2 HD 422 format used by broadcast stations. Attach an optional Extension Unit (XDCA-FS7) to open up the possibilities of multi-camera shooting and Apple ProRes 422 HQ – 1920 x 1080, which will be available early 2015 by firmware update at no additional cost. For external 4K/2K RAW synced to internal Full HD recording, connect the XDCA-FS7 to a Sony HXR-IFR5 interface and AXS-R5 recorder or compatible third party recorder. Your hand-held long-form work deserves a camera designed precisely for your purposes. You deserve the

i QFHD 3840 x 2160 at launch. 4096 x 2160 by firmware update expected early 2015. ii 59.94fps.







### Equipped with high-sensitivity 4K Super35 "Exmor" CMOS Sensor

The FS7 is equipped with a Super 35 "Exmor" CMOS Sensor with approximately 11.6 million total pixels and 8.8 million effective pixels. The high image readout speed of the image sensor allows the FS7 to support 4K motion-picture shooting and Super Slow Motion. The sensor also realizes a high sensitivity of ISO2000 and a wide dynamic range of 14 stops. Thanks to its full-pixel readout capability without pixel binning and sophisticated camera processing, jaggies and moiré are minimized.





### Full HD recording with Super Slow Motion

The FS7 offers Continuous Recording at Full HD image quality and a frame rate of up to 180fps. This makes it possible to attain up to 7.5x Super Slow Motion when played back at 23.98fps.

### 4K<sup>i</sup> internal recording at 60fps<sup>ii</sup>

The FS7 supports internal recording at 4K<sup>i</sup> resolution at a wide range of frame rates (59.94p, 50p, 29.97p, 25p, and 23.98p). When viewed on a 4K monitor, footage shot in 4K is reproduced so clearly down to the finest details that it gives a viewer the illusion of actually being within the scene.

i QFHD 3840 x 2160 at launch. 4096 x 2160 by firmware update expected early 2015. ii 59.94 fps. Furthermore, support for unlimited shooting at Super Slow Motion means no more mistimed shots leading to extra takes. It also lets you pick out footage at exactly the point that you want.

Thanks to the 4K sensor, HD recordings capture detail and image texture that HD sensor cameras cannot see.





### Supports various formats

The FS7 supports two formats, XAVC and MPEG-2 HD 422, which can be selected to suit the application. Two XAVC compression systems (IntraFrame and Long GOP) are provided through an H.264/MPEG-4 AVC codec. IntraFrame supports recording with 4:2:2 10-bit sampling for 4K and Full HD, as well as a high bit rate of up to 600 Mbps<sup>i</sup>. In Long GOP, image quality and recording time are balanced to allow Full HD shooting with 4:2:2 10-bit sampling at 50, 35 or 25 Mbps, making this format suitable for longer duration shooting. Support is also provided for the MPEG2 HD 422 recording format which is mainly used at broadcast stations around the world. Supported formats and bit rates are indicated below.

i During 4K 59.94 fps recording.



S-Log3 Original



S-Log3 Grading

## Two XQD media slots support simultaneous and relay recording

The FS7's XQD card slots consist of two channels that enable simultaneous and relay recording. During relay recording, when one media becomes full, recording continues automatically to the other media. During simultaneous recording, not only can the same footage be recorded on both channels at the same time, but also one channel can be used for random shooting while the other is being used for continuous recording as backup.

### Support for S-Gamut3.Cine/S-Log3, S-Gamut3/S-Log3 and other log curves

The FS7 supports such log gamma curves as S-Gamut3. Cine/S-Log3 and S-Gamut3/S-Log3. Due to the fact that 18% gray is set at a bright level, S-Log3 is noted for delivering a wider dynamic range than the 1300% achieved by S-log2 incorporated in camera such as the NEX-FS700, a difference equal to 1.5 stops. The log gamma itself is close to Cineon log, so color correction is easier to perform and it is possible to achieve the look of film.

In addition, compared to the color gamut of S-Gamut3. Cine, which is geared toward reproducing the wide color gamut of DCI-P3 color space used in digital cinema, the color gamut of S-Gamut3 is geared toward the reproduction of almost all actual colors, and is thereby suitable for archival purposes. Support for S-log2, which is popular among cinematographers and videographers, is scheduled to be provided in early 2015.

### Built-in ND filter unit

ND filters for adjusting the amount of light are provided in a built-in ND filter unit. This allows shooting to be done with a shallow depth of field without having to stop down the iris, even under bright conditions. The settings are Clear, 1/4 (2eV), 1/16 (4eV) and 1/64 (6eV).



### Extension Unit "XDCA-FS7" for shooting support

Extension Unit "XDCA-FS7" can be connected directly to the PXW-FS7 to enable the use of functions that support the operator's shooting style or workflow.

### RAW output for external 4K/2K RAW recording

The FS7's FS RAW Interface can be connected to an HXR-IFR5 interface unit and RAW AXS-R5 recorder to enable external 4K/2K RAW recording. The interface also allows the use of compatible third-party external recorders.

Full HD footage shot with the unit is time code-synchronized to allow offline editing of the content.

### Support for multi-camera shooting

Precise timecode synchronization provided by Genlock and Timecode In/Out functions in the XDCA-FS7 enables multi-camera operations.

### Support for Apple ProRes 422 recording

With the optional XDCA-FS7 extension unit, the PXW-FS7 enables Apple ProRes 422 HQ –  $1920 \times 1080$  recording to an XQD card in the camera.







# Hand-held comfort without rigs—or rigmarole





## Flexible design supports a wide range of shooting styles

The FS7 is equipped with a shoulder pad for stable shoulder-style shooting. Users can also choose other supported shooting styles including handy style, chest style (using the curved rear part of the FS7), tripod shooting, etc. depending on conditions.





### Ergonomic grip design

The FS7 grip, designed for easy handling and operability, is the result of exhaustive consultation with videographers and cinematographers, as well as the production of various prototypes. The shape supports long periods of camera use and flexibly accommodates subtle differences among various users' gripping styles.

The angle of the grip can be easily adjusted with the press of a button. In addition to a zoom button and Rec Start/Stop, the grip also has several programmable buttons that can be customized for easy access to any other functions such as the focus magnifier function.



## Arm adjusts to user's physique and shooting posture

The length of the arm section of the FS7 can be adjusted just by turning a knob. Another knob at the joint makes it easy to adjust the angle of the camera. So a user can choose a comfortable style that suits his or her physique and shooting position.



# Putting you in control

Controls are concentrated on the inside panel to make adjustments easy even during on-the-shoulder shooting.



### Viewfinder

### Adjustable with degrees of freedom for easy confirmation of image quality

The Peaking and Zebra function buttons and contrast knob are positioned on the side of the FS7 viewfinder for easy adjustment of focus, contrast and exposure. Also, by turning a single knob, the position of the finder can be set, allowing for degrees of freedom. The finder is designed so that people with a dominant left eye can also use it comfortably.





### Dust and moisture resistance for use even in harsh environments

The FS7 is constructed with buttons, dials and other parts specially sealed to prevent dust and water spray from entering. In addition, the cooling fan is equipped with a special duct that prevents dust and water spray from entering electric components and cool air is transmitted to the heat sink to lower accumulated temperatures. In these and other ways, the body of the FS7 is constructed to withstand tough conditions.



### Built-in Multi-Interface (MI) Shoe

The FS7 is equipped with a Multi-Interface (MI) Shoe that supports connection to wireless microphone packages such as the UWP-D11 or UWP-D12 (sold separately). When connected to the shoe, the HVL-LBPC light (sold separately) can be turned on or off from the camera, and power and audio connections are provided to the UWP-D11 or UWP-D12 without cables.



# $\alpha$ Mount System for a Wide Selection of Lenses

### Adopts E-mount that is suitable for movie shooting

The FS7 incorporates the E-mount lens mount. This is especially useful for motion-picture shooting because the system supports power driven silent auto focus, iris control, power zoom and more, as well as SteadyShot image stabilization and other functions. Moreover, the E-mount system's short flange-back distance (the distance from the lens-mounting surface to the image sensor) enables use of A-mount lenses via LA-EA4 or LA-EA3 lens adapter, as well as various other lenses via third-party adapters. The E-mount system thereby makes it possible to take advantage of a wealth of lens resources suitable for creative, versatile video expression.

#### Zoom

Zooming is a fundamental moviemaking technique that is used for both practical framing changes as well as creative effect. "Smooth" is the key requirement here. Any tracking irregularities such as jitter or axial image shifts are unacceptable. Sony's professional camera technology combines with state-of-the-art lens design and control technologies once again to deliver exceptionally smooth tracking throughout the zoom range at any speed. And, like focus operation, zooming is quiet as well as responsive thanks to advanced mechanical and actuator design and manufacture. Lenses are individually tested to ensure that the desired level of performance is achieved in every unit.

#### Iris

Background bokeh (defocusing) can be just as important in movies as it is in still images. The original Sony's circular

aperture design contributes to smooth, beautiful bokeh with natural highlights. Iris noise can be an issue for moviemaking too, so the quietest, most accurate and responsive control and actuator systems are used for iris operation as well.



#### Focus

When making movies you're frequently focusing while shooting, either with autofocus or manually. A lens that has not been designed with movies in mind might exhibit "breathing," or variations in the angle of view while focusing. That can be a jarring distraction, so Sony  $\alpha$  mount lenses feature optical designs and control technology inherited from our professional camera that ensure an absolute minimum of breathing. Noise while focusing can also be an issue, but advanced Sony's linear motor and lens control technologies achieve quiet focusing that is also extremely responsive. Part of the reason that focus control is so quiet is that original Sony linear motors are contactless, with no gears or mechanical coupling to generate noise. Internal focusing is an advantage too, since the front element of the lens does not rotate and the overall length of the lens does not change while focusing. S ED ( IF OSS SSM SMO PZ

Distance scale

Focusing ring

Zoom ring

G



Aperture scale

POWER ZOOM lever

Lens mounting index

Shake compensation

ZOOM switch

Iris ring

This top-quality powered zoom lens for 35mm fullframe format cameras has been created to satisfy professional moviemaking requirements, including the high resolution 4K format. Focus breathing and zoom image shift have been reduced to an absolute minimum, while aspherical elements and advanced multi-coating technology effectively suppress aberration. Quiet operation is also a priority, so an SSM (Super Sonic wave Motor) drive system has been employed for precise, quiet zooming. Independent control rings for zoom, focus, and aperture are provided for the first time in an lpha lens. Built-in Optical SteadyShot image stabilization adds to the extraordinary performance of this outstanding lens.



Lens groups/elements: 12 / 18 Minimum focus: 0.4 m (AF) / 0.95 m (MF) 0.95 m (MF) Filter diameter: 95 mm Size: 105 mm (diameter) x 162.5 mm (length) Weight: approx. 1215 g (without tripod mount)

135 mm focal length

Ω Δ

• Aspherical lens • ED glass



F8

Max. aperture - R 10 line pairs/mm - T 10 line pairs/mm R 30 line pairs/mm T 30 line pairs/mm



8 12 Distance from center of image (mm)

16 20

R 10 line pairs/mm T 10 line pairs/mm R 30 line pairs/mm T 30 line pairs/mm (R: radial target, T: tangential target)



#### E. Sonnar T\* E 24mm F1.8 ZA SEL24F18Z -C 🛞 ED ( IF





65.5 mm (length) ■ Weight: approx. 225 g

📷 🖬 35 mm full-frame format 🛛 🕼 Circular aperture 📖 😇 ED(Extra-low Dispersion) glass / Super ED 🔢 🚺 Aspherical lens / Advanced aspherical lens

💀 Coading Nano AR Coating 📧 Internal focusing 📧 Rear focusing 🛤 🛤 Focus range limiter / Electronic Focus range limiter 📠 Focus hold button 🗛 Outen Auto clutch

#### 11

#### **Specifications**

General	
Weight	Approx. 4lbs 7oz (2.0 kg) (body only)
	Approx. 10 lbs (4.5 kg) (with Viewfinder, Eyepiece, Grip Remote Control, BP-U30 battery, SELP28135G LENS, an XQD memory card)
Dimensions (W x H x D)*	6 1/8 x 9 13/32 x 9 23/32 in. (156 x 239 x 247 mm) (body without protrusions)
Power Requirements	DC 12 V
Power Consumption	Approx. 19 W (while recording XAVC-I QFHD 59.94P, SELP28135G Lens, Viewfinder ON, not using external device)
Operating lemperature Storage Tomporature	32°F to 104°F (0°C to 40°C)
Batteny Operating Time	-4 F 10 + 140 F (-20 C 10 + 00 C)
building time	(while recording XAVC-I QFID 59.94P, SELP28135G Lens, Viewfinder ON, not using external device)
	Approx. 2 hrs with BP-000 battery (while recording XAVC-I QFHD 59.94P, SELP28135G Lens, Viewfinder ON, not using external device)
	Approx. 3 hrs with BP-U90 battery (while recording XAVC-I QFHD 59.94P, SELP28135G Lens, Viewfinder ON, not using external device)
Recording Format (Video)	<xavc intra=""></xavc>
	XAVC-I mode:QFHD 59.94P, CBG, bit rate 600Mbps, MPEG-4 H.264/AVC
	XAVC-I mode: QFHD 50P, CBG, bit rate 500Mbps, MPEG-4 H.264/AVC
	XAVC-I IIIOUE.QFRD 29.97P, CBG, bit rate 240Mbps, MPEG-4 H.204/AVC
	XAVC-I mode: QEHD 25P, CBG, bit rate 250Mbps, MPEG-4 H 264/AVC
	XAVC-I mode:HD 59.94P. VBR. maximum bit rate 222Mbps. MPEG-4 H.264/AVC
	XAVC-I mode:HD 50P, VBR, maximum bit rate 185Mbps, MPEG-4 H.264/AVC
	XAVC-I mode:HD 59.94i, VBR, maximum bit rate 111Mbps, MPEG-4 H.264/AVC
	XAVC-I mode:HD 50i, VBR, maximum bit rate 112Mbps, MPEG-4 H.264/AVC
	XAVC-I mode:HD 29.97P, VBR, maximum bit rate 111Mbps, MPEG-4 H.264/AVC
	XAVC-I mode:HD 23.98P, VBR, maximum bit rate 89Mbps, MPEG-4 H.264/AVC
	XAVC-I mode:HD 20P, VBK, moximum bit rate 112/Wbps, WPEG-4 H.204/AVC
	XAVCLORES AVC. A Composition of the second state and the second state an
	XAVC-L GEHD 29.7747/30F Hidde: VBR, Hiddinian bir are 130mbps, MFEO-4 H.204/AVC
	XAVC-LHD 50 mode: VBR. maximum bit rate 50Mbps. MPEG-4 H 264/AVC
	XAVC-L HD 35 mode: VBR. maximum bit rate 35Mbps. MPEG-4 H.264/AVC
	XAVC-L HD 25 mode: VBR, maximum bit rate 25Mbps, MPEG-4 H.264/AVC
	<mpeg-2 gop="" long=""></mpeg-2>
	MPEG HD422 mode: CBR, maximum bit rate 50Mbps, MPEG-2 422P@HL
Recording Format (Audio)	LPCM 24 bits, 48 kHz, 4 channels (Recording/Playback ONLY 2channels)
Recording Frame Rate	<aavg inito=""></aavg>
	XAVC-1 &FD 11008: 3040X2100/ 39.94P, 30P, 29.97P, 23.90P, 23P XAVC-1 HD mode: 1020v1080/50 0/P 50P 50 0/I; 50I 20 07P 23 08P 25P
	XAVO FID HIDDE: 1720x1000(07.54),001,07.54,00,27.771,20.701,201
	XAVC-L QFHD mode: 3840x2160/59.94P, 50P, 29.97P, 23.98P, 25P
	XAVC-L HD 50 mode: 1920x1080/59.94P, 50P, 59.94i, 50i, 29.97P, 23.98P, 25P
	XAVC-L 35 mode: 1920x1080/59.94P, 50P, 59.94i, 50i, 29.97P, 23.98P, 25P
	XAVC-L 25 mode: 1920x1080/59.94i, 50i
	<pre><mpeg-2 gop="" long=""></mpeg-2></pre>
	MPEG HD422 mode: 1920x1080/59.941, 501, 29.97P, 23.98P, 25P 1280x720/59.94P, 50P, 29.97P, 23.98P, 25P
Recordina/Playback Time	<xavc intro=""></xavc>
	XAVC-I mode QFHD 59.94P
	When using QD-G128A (128GB): Approx. 22 minutes, When using QD-G64A (64GB): Approx. 11 minutes
	XAVC-I mode QFHD 50P
	When using QD-G128A (128GB): Approx. 20 minutes, when using QD-G04A (04GB): Approx. 13 minutes
	When using QD-G1284 (128GB): Approx 44 minutes When using QD-G644 (64GB): Approx 22 minutes
	XAVC-I mode QFHD 23.98P
	When using QD-G128A (128GB): Approx. 55 minutes, When using QD-G64A (64GB): Approx. 27 minutes
	When using QD-G128A (128GB): Approx 52 minutes When using QD-G64A (64GB): Approx 26 minutes
	XAVC-I mode HD 59.94P
	When using QD-G128A (128GB): Approx. 59 minutes, When using QD-G64A (64GB): Approx. 30 minutes
	XAVC-I mode HD 50P
	When using QD-G128A (128GB): Approx. 71 minutes, When using QD-G64A (64GB): Approx. 35 minutes
	When using QD-G128A (128GR): Approx 118 minutes When using QD-G64A (64GR): Approx 59 minutes
	XAVC-I mode HD 50i
	When using QD-G128A (128GB): Approx. 141 minutes, When using QD-G64A (64GB): Approx. 70 minutes
	XAVC-I mode HD 29.97P
	When using QD-G128A (128GB): Approx. 118 minutes, When using QD-G64A (64GB): Approx. 59 minutes
	XAVG-I mode HD 23.98P When using OD C139A (139CD), Annoy 147 minutes When using OD C44A (44CD), Annoy 74 minutes
	XAVC-I mode HD 25P
	When using QD-G128A (128GB): Approx. 141 minutes, When using QD-G64A (64GB): Approx. 70 minutes
	<xavc long=""></xavc>
	XAVC-L mode QFHD 59.94P/50P When using OD G128A (128GR): Approx 87 minutes When using OD G64A (64CR): Approx 44 minutes
	XAVC-L mode DEHD 29 97P/23 98P/25P mode:
	When using QD-G128A (128GB): Approx, 131 minutes. When using QD-G64A(64GB): Approx, 66 minutes
	XAVC-L 50 mode
	When using QD-G128A (128GB): Approx. 262 minutes, When using QD-G64A (64GB): Approx. 131 minutes
	XAVC-L 35 mode
	when using QD-G64A (64GB): Approx. 374 minutes, When using QD-G64A (64GB): Approx. 187 minutes
	When using QD-G128A (128GB): Approx. 524 minutes When using QD-G644A (64GB): Approx. 262 minutes
	MPEG HD422 mode
	When using QD-G128A (128GB): Approx. 262 minutes, When using QD-G64A (64GB): Approx. 131 minutes

Lens Mount	E-mount
Camera Section	
Imaging Device (Type)	Super35 type Single-chip Exmor CMOS
Effective Picture Elements	17:9 4096 (H) x 2160 (V)
	16:9 3840 (H) x 2160 (V)
Built-in Optical Filters	OFF: Clear, 1/4ND, 1/16ND, 1/64ND
Sensitivity (2000 lx, 89,9% reflectance)	Video Gamma: T14 (3840 x 2160/23.98P mode 3200K)
ISO Sensitivity	ISO 2000 (S-Loa3 Gamma D55 Light source)
Minimum Illumination	0.7 lx (+18dB 23.98P Shutter OFE ND Clear F1.4)
S/N Ratio	57 dB (Y) (typical)
Shutter Speed	1/3 sec to 1/9.000 sec
Slow & Quick Motion Function	XAVC-I mode 3840x2160: 1 to 60 frames (59.94P 50P 29.97P 23.98P 25P)
	XAVC-I mode 1920x1080: 1 to 180 frames (59.94P 29.97P 23.98P) 1 to 150 frames (50P 25P)
	XAVC-1 mode 3840x2160: 1 to 60 frames (59 94P 50P 29 97P 23 98P 25P)
	XAVC-1 mode 1920x1080:1 to 120 frames (59 94P 50P 29 97P 23 98P 25P)
White Balance	Preset Memory & Memory B (1500K-50000K)/ATW
Gain	-3 0 3 6 9 12 18 dB AGC
Gamma Curve	STD HG Llear SJ on 3
Input/Output	010, 110, 0301, 0 10g0
Audio Input	VLD type 3 pin (female) (v2), line (min/min, v48.)/ celestable, Min Deferences, 40, 50, 60dBu
Pol Output	ALK-Type 3-pin (remule) (A2), me/mic/mic +40 v selectuble, Mic Reletence, -40, -30, -000bu
SDI Output	SMTPE292M/424M/425M
USB	USB device, mini-B (x1)
Headphone Output	Stereo mini jack (x1), -16dBu 16Ω
Speaker Output	Monaural
DC Input	DC jack
Remote	Stereo mini-minijack (ø2.5 mm)
HDMI Output	Type A (x1)
Option	4-pin, Type A for W-LAN (x1)
Monitorina	
Built-in LCD Monitor	8.8 cm (3.5 type), Approx, 1.56M dots
Built-in Microphone	
	Omni-directional monoral electret condenser microphone.
Media	
Туре	XAD Card slot (x2)
	SD Card slot (x1) for saving configuration data
	Boyd Cap (1)
	Viewfinder (1)
	Eveniece (1)
	Grip Pemote Control (1)
	USB wireless LAN module IFLWLM3 (1)
	Wireless remate commander (1) (DMT 9/5)
	Windersteinung Gemeinzungen (1) (KWI-043)
	MPA A01 AC Adapter (1)
	MPA-AGT AG ADUPLET (1)
	BU-OF barrery charger (1)
	BP-USU battery pack (1)
	Power cord (2)
	USB coble (1)

#### Accessories

\* The values for dimensions are app





Operating Guide (2) CD-ROM "Manuales 1





HVL-LBPC Battery Video Light

ior Solid-State Memory Cam



required for cable-free op with UWP-D11/UWP-D12





ECM-MS2 Electret Condenser Microphone

©2014 Sony Corporation. All rights reserved.

trademarks of Sony Corporation.

The values for mass and dimension are approximate. Sony and Sony logo are trademarks of Sony Corporation. XQD logo is a trademark of CompactFlash Association.

Reproduction in whole or in part without written permission is prohibited. Features and specifications are subject to change without notice.

XDCAM, MPEG HD422, XAVC,  $\alpha$  Mount System and their respective logos are

All other trademarks are the property of their respective owners.

QD-G32A XQD Memory Card



VCT-FS7 Light Weight Rod Support

**Dimensions** 





SON O 40 00-10. 3/16 (132) 0 0 oœŏ 0 7 15/16 (202.1) 8 5/8 (220.1) 9 1/2 (241.3)

Unit: inches (mm)

sony.com/professional V-2616 (MK11159V1)

Sony Electronics Inc.

Park Ridge, NJ 07656

1 Sony Drive